




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04R 25/00, A61F 11/04		A1	(11) International Publication Number: WO 96/34508
			(43) International Publication Date: 31 October 1996 (31.10.96)
(21) International Application Number: PCT/US96/05854		(81) Designated States: AU, CA, JP, US, European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(22) International Filing Date: 23 April 1996 (23.04.96)			
(30) Priority Data: 08/429,749 26 April 1995 (26.04.95) US		Published <i>With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>	
(60) Parent Application or Grant (63) Related by Continuation US 08/429,749 (CIP) Filed on 26 April 1995 (26.04.95)			
(71) Applicant (for all designated States except US): ADVANCED BIONICS CORPORATION [US/US]; 12740 San Fernando Road, Sylmar, CA 91342 (US).			
(72) Inventors; and (75) Inventors/Applicants (for US only): LOEB, Gerald, E. [US/CA]; 90 Bagot Street, Kingston, Ontario K7L 3E5 (CA). FALTYS, Michael, A. [US/US]; 19235 Celtic Street, Northridge, CA 91326 (US).			
(74) Agents: SAMPLES, Kenneth, H. et al.; Fitch, Even, Tabin & Flannery, Room 900, 135 S. LaSalle Street, Chicago, IL 60603 (US).			

(54) Title: A MULTICHANNEL COCHLEAR PROSTHESIS WITH FLEXIBLE CONTROL OF STIMULUS WAVEFORMS



(57) Abstract

A method and system provides for a wide range of temporospatial patterns of electrical stimulation waveforms to be readily specified for respective channels of a multichannel cochlear prosthesis. The cochlear prosthesis includes: a speech processor system (10), and a cochlear stimulator (12). The speech processor system typically includes an external headpiece (14), including a microphone (18), coupled to a speech processor (16). The speech processor (16) includes electronic circuitry, typically including a microprocessor, that converts acoustical signals sensed through the microphone to electrical signals, and processes the electrical signals in accordance with a desired speech processing strategy. The definition of simple or complex stimulation waveforms to be used as part of the selected speech processing strategy is facilitated, in a preferred embodiment, through the use of a template table (e.g., Fig. 8) stored in the speech processor. The rows and columns of the template table define time intervals and stimulation channels (and hence stimulation sites). The individual cells of the template table are programmed, e.g., using a laptop computer (17), to contain selected alphanumeric codes or characters, including null characters, that define the polarity and relative magnitude of desired stimulation patterns and waveforms that are applied to the defined stimulation sites at the indicated frame times. Alternatively, the stimulation patterns and waveforms may be specified in a list of spatial/temporal events.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AM	Armenia	GB	United Kingdom	MW	Malawi
AT	Austria	GE	Georgia	MX	Mexico
AU	Australia	GN	Guinea	NE	Niger
BB	Barbados	GR	Greece	NL	Netherlands
BE	Belgium	HU	Hungary	NO	Norway
BF	Burkina Faso	IE	Ireland	NZ	New Zealand
BG	Bulgaria	IT	Italy	PL	Poland
BJ	Benin	JP	Japan	PT	Portugal
BR	Brazil	KE	Kenya	RO	Romania
BY	Belarus	KG	Kyrgyzstan	RU	Russian Federation
CA	Canada	KP	Democratic People's Republic of Korea	SD	Sudan
CF	Central African Republic	KR	Republic of Korea	SE	Sweden
CG	Congo	KZ	Kazakhstan	SG	Singapore
CH	Switzerland	LI	Liechtenstein	SI	Slovenia
CI	Côte d'Ivoire	LK	Sri Lanka	SK	Slovakia
CM	Cameroon	LR	Liberia	SN	Senegal
CN	China	LT	Lithuania	SZ	Swaziland
CS	Czechoslovakia	LU	Luxembourg	TD	Chad
CZ	Czech Republic	LV	Latvia	TG	Togo
DE	Germany	MC	Monaco	TJ	Tajikistan
DK	Denmark	MD	Republic of Moldova	TT	Trinidad and Tobago
EE	Estonia	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	UG	Uganda
FI	Finland	MN	Mongolia	US	United States of America
FR	France	MR	Mauritania	UZ	Uzbekistan
GA	Gabon			VN	Viet Nam

**A MULTICHANNEL COCHLEAR PROSTHESIS
WITH FLEXIBLE CONTROL OF STIMULUS WAVEFORMS**

Background of the Invention

5 The present invention relates to multichannel cochlear prosthesis, and more particularly to a multichannel cochlear prosthesis that offers flexible control of the stimulus waveforms.

10 Cochlear prostheses produce sensations of sound in deaf patients by direct electrical stimulation of the auditory nerve. In modern, multichannel cochlear prostheses, several different sites are stimulated at various distances along the cochlea to evoke the different pitches of sound perception that are normally
15 encoded by nerve activity originating from the respective sites. The patterns of electrical stimulation are derived from acoustic signals picked up by a microphone and transformed by a so-called speech processor that is programmed to meet the particular requirements of each
20 patient. Several different schemes for processing the acoustic signal and transforming it into electrical stimuli have been developed and are well-described in the scientific literature and various patents. All of these schemes can be divided into two basic types on the basis
25 of the waveforms of the electrical stimuli:

 i) Analog waveforms, which are essentially filtered versions of the continuous acoustic waveform, usually involving dynamic range compression, bandpass filtering and scaling to the
30 stimulus current ranges that evoke a satisfactory range of auditory sensations from threshold of perception to maximal comfortable loudness. This produces a rich but poorly controlled set of resultant waveforms.

35 ii) Biphasic pulses, which consist of a single cycle of a square wave in which current flows in one direction at a specified magnitude and for a specified brief period of time and is followed

- 2 -

immediately by an opposite direction of current of a similar magnitude and duration. These pulses are most often delivered in sequence to various sites, with the instantaneous magnitude at each site proportional to some measure of the amount of energy present in a particular frequency band of the acoustic waveform. The result is an impoverished but precisely controlled set of stimulus waveforms.

Both of these stimulus waveform types have been selected because they are relatively easy to produce and modulate electronically for real-time encoding of speech and because they guarantee a charge-balanced alternating current at the electrodes, avoiding net direct current that is known to cause electrolytic damage to both electrodes and body tissues.

Recent findings regarding the complex biophysical phenomena associated with the electrical excitation of neurons and psychophysical phenomena regarding the interpretation of neural activity by the auditory nervous system suggest that the quality and intelligibility of speech percepts evoked by a cochlear prosthesis may be improved in a given patient by more specific manipulations of the electrical stimulus waveforms tailored to that patient. In particular, more complex sequences of polarities, with or without pauses between phases and sites, and with or without simultaneous current delivery at more than one site, appear to be desirable. There is thus a need in the art for a cochlear stimulation system that allows complex stimulation waveforms to be individually tailored for each stimulation site.

- 3 -

Summary of the Invention

The present invention provides a method and/or system whereby a rich set of temporospatial patterns of electrical stimulation can be tested by an audiologist in the process of fitting the cochlear prosthesis, and in which desirable patterns of pulsatile stimuli of almost arbitrary complexity can be modulated in real-time by the acoustic signal to produce useful perceptions of sound in otherwise deaf patients.

10 In order to implement the present invention, a cochlear stimulation system is required. Such cochlear system typically includes two main components: (1) a speech processor (SP), and (2) an implantable system. The speech processor is typically an external system (but 15 may also be part of the implanted system). When the speech processor is an external system, it is coupled to a headpiece. The speech processor includes a battery, or equivalent power source, and further includes electronic circuitry, typically including a microprocessor, that 20 converts sensed acoustical signals to electrical signals and processes the electrical signals in accordance with a desired speech processing strategy. It is a feature of the present invention to facilitate the definition of complex stimulation waveforms to be used as part of the 25 selected speech processing strategy, thereby enhancing the ability of the system to produce useful perceptions of sound for a deaf patient.

The headpiece, which is typically adapted to be worn by a patient in or behind the ear, includes a 30 microphone for sensing the acoustical signals and converting them to electrical signals, and further includes an antenna, or coil, for transmitting the processed signals to, and receiving signals from, the implantable system.

- 4 -

The implantable system is adapted to be implanted so that it can readily receive signals from, and (in some embodiments) send signals to, the externally-worn headpiece and/or other external components. Typically, the implantable system, frequently referred to as an implantable cochlear stimulator (ICS), contains no power source, but rather receives its operating power from the signals that are coupled or transmitted to it from the wearable system. However, it is to be emphasized that the present invention is not limited to an ICS that is powered only from the external system, but applies to any implantable stimulation system that is controlled by an external system or that operates autonomously by means of batteries and internal means for detecting and processing sound information.

The implantable system or ICS employs a multiplicity of electrical current sources, each connected to at least one electrode contact that defines a stimulation site within the cochlea. Electronic circuitry is also included in the implantable system that permits the sign (polarity) and magnitude of the output current of each of the current sources to be electronically re-specified at frequent or other specified intervals.

In operation, the speech processor defines or specifies the complex stimulation waveforms that are to be used by the ICS, and transmits such definition/specification to the ICS at frequent, predetermined intervals. The ICS responds by generating such complex stimulation waveforms at the times, and for the durations, indicated in the received definition/specification, and then applying such generated waveforms to designated tissue sites, i.e., to

- 5 -

specific electrode contacts that are positioned within the cochlea (or other living tissue).

In accordance with one aspect of the invention, a template of the desired temporal sequence of output
5 currents from the various current sources within the ICS is stored digitally within the speech processor as a table of weighting coefficients (or weighting factors) whose columns (or, alternatively, rows) represent the different current sources, or "channels", of the ICS, and
10 whose rows (or, alternatively, columns) represent intervals of time. The "channels" and increments of time thus form the two ordinates of the table. Such table may also contain additional columns that control other aspects of the stimulation, such as the connection of
15 electrode contacts to the current sources. The template thus consists of a modest number of intervals (typically 20-100) whose total duration defines a "cycle" of stimulation. At the beginning of each new stimulation cycle, for example, information derived from the
20 acoustical signal during a previous cycle (or other data-gathering time period) is used to compute the magnitude of stimulation required for each of the current sources of the ICS during the new cycle. In each successive interval of the new cycle, the instantaneous current flow
25 to be generated from each of the current sources during the new cycle is determined by multiplying the magnitude of stimulation by the corresponding weighting factor that is stored in the table. Such information is transferred to the ICS during each interval of the new cycle, where
30 it is acted upon by the electronic circuitry within the ICS to generate the specified instantaneous current flow at the appropriate time.

The present invention may thus be characterized as a multichannel cochlear prosthesis system that
35 includes: (1) a speech processor; (2) a cochlear

- 6 -

stimulator; and (3) means for coupling the speech processor and the cochlear stimulator together so that data signals and control signals may be passed therebetween. The speech processor includes:

- 5 (i) template storage means for storing a set of coefficients that represent a particular temporospatial pattern of stimulus waveforms, and (ii) means responsive to the set of coefficients stored in the template storage means for generating data and control signals that
- 10 specify a particular temporospatial pattern of controlled stimulus waveforms to be generated by respective channels within the cochlear stimulator. The cochlear stimulator includes: (i) means for receiving said data and control signals from the speech processor, (ii) a multiplicity of
- 15 channels, each having at least one pair of electrodes associated therewith, (iii) means for generating a controlled stimulus waveform for each of the multiplicity of channels as a function of said data and control signals received from the speech processor, and
- 20 (iv) means for applying the controlled stimulus waveform to at least two of the multiplicity of channels so that the specified controlled stimulus waveform appears across the paired electrodes of at least two channels.

It is thus a feature of the present invention

25 to facilitate the definition/specification of a wide range of different temporospatial patterns of electrical stimulation current that can be generated by an implantable cochlear stimulator.

It is another feature of the invention to allow

30 complex stimulation waveforms to be defined/specified in a simple manner.

It is yet an additional feature of the invention, in accordance with one aspect thereof, to allow the definition/specification of the stimulation

35 current to be created simply by writing appropriate

- 7 -

numbers or data values (e.g., alphanumeric values) into a table that defines a current stimulation template, with one of the rows or columns of the table defining time, and with the other of the rows or columns defining
5 electrode pairs (which electrode pairs, once implanted, define specific stimulation sites within the cochlea). Thus, the intersection of a given row and column of the table simply specifies the magnitude, polarity, and time during which the specified stimulation current is applied
10 to one or more given electrode pairs (stimulation site).

It is a further feature of the invention to allow the cycles of stimulation information that are sent to an implanted stimulator to be selectively shortened so that the stimulation information on higher frequency
15 channels can be sent at a higher rate, while lower frequency channels can be updated less frequently.

Brief Description of the Drawings

The above and other aspects, features and
20 advantages of the present invention will be more apparent from the following more particular description thereof, presented in conjunction with the following drawings wherein:

FIG. 1 shows the main elements of a cochlear
25 stimulation system;

FIG. 2 is a partial functional block diagram of the wearable and implantable portions of the system of FIG. 1;

FIG. 3 shows a block diagram of the wearable
30 and implantable portions of the system of FIG. 1 in accordance with a preferred embodiment thereof;

FIG. 4 shows the makeup of a data frame used with the preferred system of FIG. 3;

FIG. 5 illustrates how multiple data frames are
35 used with the system of FIG. 3 in order to achieve a

- 8 -

desired stimulation pattern that repeats itself in cycles;

FIG. 6 illustrates a simple biphasic CIS stimulation template for use with the present invention that provides a CIS stimulation pattern for an eight-channel stimulator device;

FIG. 7 shows the stimulation template for a somewhat more complex biphasic stimulation pattern that includes time delays between phases and channels;

FIG. 8 depicts the stimulation template for a much more complex stimulation pattern that includes asymmetrical and triphasic pulses;

FIG. 9 shows the stimulation template for a stimulation pattern that includes "alterphasic" pulses in which charge balance is achieved by two monophasic pulses with opposite polarity presented at different times in the cycle;

FIG. 10 illustrates the stimulation template for a stimulation pattern that includes more frequent narrow biphasic stimulation pulses in some channels, and less frequent wider biphasic stimulation pulses in other channels;

FIG. 11 depicts the stimulation template for a stimulation pattern that provides simultaneous or substantially overlapping biphasic pulses on two or more channels;

FIG. 12A shows the stimulation template for a stimulation pattern that uses short-interval transmissions to create narrow pulses and a faster overall cycle rate;

FIG. 12B illustrates an example of a virtual channel stimulation template that may be used to create two virtual channels by mapping information from eight channels into only six output stages; and

- 9 -

FIG. 13 is a simplified flow chart that shows how the above or other stimulation templates may be used within the speech processor portion of the invention to control the stimulation current patterns generated by the implantable stimulator portion of the invention.

Corresponding reference characters indicate corresponding components throughout the several views of the drawings.

10 Detailed Description of the Invention

The following description is of the best mode presently contemplated for carrying out the invention. This description is not to be taken in a limiting sense, but is made merely for the purpose of describing the general principles of the invention. The scope of the invention should be determined with reference to the claims.

The present invention relates to a method and system for permitting a wide variety of complex stimulation patterns and waveforms to be used by a multi-channel implantable cochlear stimulator. A preferred multi-channel cochlear stimulator of the type that may be used by the invention is described in U.S. Patent Application No. 08/322,065, filed 10/12/94, which patent application is incorporated herein by reference. It is to be understood, however, that the invention is not limited to use only by the type of stimulator described in the cited patent application, but may be used with any multi-channel stimulator that includes the ability to set a prescribed pattern of stimulation waveforms for each channel of the stimulator.

Turning to FIG. 1, there is shown a cochlear stimulation system that includes an external portion 10 and an implantable portion 12. The external portion includes a speech processor 16 (which may also be

- 10 -

referred to as a wearable processor 16), and a headpiece 14. The implantable portion includes an implantable cochlear stimulator (ICS) 21, and an electrode array 48. The electrode array 48 is adapted to be inserted within the cochlea of a patient. The array 48 includes a multiplicity of electrodes spaced along its length that are selectively connected to the ICS 21. The electrode array 48 may be substantially as shown and described in U.S. Patent No. 4,819,647, incorporated herein by reference. Electronic circuitry within the ICS 21 allows a specified stimulation current to be applied to selected pairs or groups of the individual electrodes included within the electrode array 48 in accordance with a specified stimulation pattern, defined by the speech processor 16.

The ICS 21 and the headpiece 14 each include an antenna coil. In operation, i.e., when the ICS has been implanted and the headpiece 14 is positioned to be aligned over the location where the ICS is implanted, such coils are inductively coupled to each other, thereby allowing information (e.g., the magnitude and polarity of a stimulation current) and power to be transmitted from the speech processor 16 to the ICS 21. Some models of the ICS 21 also permit information to be transmitted from the ICS 21 back to the speech processor 16.

The headpiece 14 also includes a microphone 18 that senses acoustic signals and converts such sensed signals to corresponding electrical signals. The speech processor 16 processes these converted acoustic signals in accordance with a specified speech processing strategy in order to generate appropriate control signals for controlling the ICS. Such control signals specify or define the polarity, magnitude, location (which electrode pair receives the stimulation current), and timing (when

- 11 -

the stimulation current is applied to the electrode pair) of the stimulation current that is generated by the ICS.

It is common in the cochlear stimulator art to condition the magnitude and polarity of the stimulation
5 current applied to the implanted electrodes in accordance with a specified stimulation strategy. Such stimulation strategy involves defining a pattern of stimulation waveforms that are to be applied to the electrodes as controlled electrical currents. For example, it is
10 common to apply a biphasic stimulation pulse to a given electrode pair, having a magnitude that varies as a function of the sensed acoustic signal. (A "biphasic" pulse is generally considered as two pulses: a first pulse of one polarity having a specified magnitude,
15 followed immediately, or after a very short delay, by a second pulse of the opposite polarity having the same total charge, which charge is the product of stimulus current times duration of each pulse or phase.) If multiple electrode pairs exist, as is the case with a
20 multi-channel cochlear stimulator, then it is also common to sample the acoustic signal at a rapid rate, and apply a biphasic stimulation pulse in sequence to each of the pairs of electrodes in accordance with a specified pattern and cycle time, with the magnitude of the
25 stimulation current being a function of information contained within the sensed acoustic signal at a given (e.g., the most recent) sample time.

Heretofore, all known stimulation systems have been severely limited in their ability to specify more
30 than one or two stimulation patterns for use with the implantable stimulator. Moreover, what patterns have been available have been limited to very simple stimulation waveforms, e.g., sequencing through each electrode pair in a fixed sequence with simple biphasic
35 pulses of varying amplitude, or sequencing through each

- 12 -

electrode pair in a fixed sequence with simple biphasic pulses of varying width. There are no cochlear stimulation systems known to applicants that permit complex stimulation waveforms to be individually tailored
5 for each stimulation site (where each "stimulation site" corresponds to a selected electrode pair). The present invention advantageously overcomes this limitation by providing an almost infinite variety of complex stimulation waveforms that can be easily specified and
10 thereafter generated by the implantable stimulator. Such flexibility in defining or specifying the stimulation patterns thus allows the audiologist, or other medical personnel who is fitting the implantable unit, to readily customize the stimulation patterns and waveforms used by
15 the stimulation system to be optimized for a particular patient.

Still referring to FIG. 1, it is seen that a laptop computer 17, or other type of computer, or equivalent device, may be coupled to the speech processor
20 16 in accordance with the present invention. Such laptop computer 17 (or equivalent device) provides a display screen 15 on which stimulation templates and other information may be displayed and defined. Such computer 17 thus provides a very simple way for the audiologist or
25 other medical personnel, or even the patient, to easily specify a particular pattern of stimulation waveforms that may be thereafter used, even if for just a short testing period, regardless of whether such stimulation pattern is simple or complex. Also shown in FIG. 1 is a
30 printer 19 which may be connected to the computer 17 if desired in order to allow a record of the stimulation templates and pattern(s) that have been specified to be printed.

Turning next to FIG. 2, a partial functional
35 block diagram of the external or wearable portion 10' and

- 13 -

the implantable portion 12' of the stimulation system of Fig. 1 is shown. It is to be emphasized that what is shown in FIG. 2 depicts the functions that are carried out by either the external portion 10' or the implantable portion 12'. The actual electronic circuitry that is used to carry out these functions is not critical to the present invention, although a representation of a preferred embodiment of such circuitry is shown below in FIG. 3 and in the cited patent application. It should also be pointed out that the particular functions shown in FIG. 2 are representative of just one type of signal processing strategy that may be employed (relating to dividing the incoming signal into frequency bands, and independently processing each band). Other signal processing strategies could just as easily be used to process the incoming acoustical signal, and the present invention could still be used to provide added flexibility in specifying the stimulation patterns and waveforms that are used.

In FIG. 2, it is seen that the external portion 18 includes a microphone 18 to sense acoustical information and convert it to electrical signals. These signals are then amplified in audio front-end circuitry 22, which includes an amplifier having automatic gain control, and typically also includes a manual "sensitivity" control. The amplified audio signal is then converted to a digital signal by analog-to-digital (A/D) converter 28'. The resulting digital signal is then processed in one of a multiplicity of digital signal processing channels. For example, eight separate channels may be used, each responding to a different frequency content of the sensed acoustical signal. That is, the incoming signal is divided into a multiplicity of frequency channels, as defined by respective bandpass filters included within a filter bank 24.

- 14 -

Except for the frequency band of the individual filters 24', each of the channels into which the incoming signal is divided are virtually identical. Hence, only one such channel will be described herein. After passing
5 through its respective bandpass filter 24', the envelope of the resulting signal is detected using envelope detection circuitry 50. This signal is then amplified by amplifier 52. A VU meter 56 may then be used to graphically display the amount of signal energy present
10 within the band. The signal is then mapped to an appropriate magnitude, using mapping circuitry 54, depending upon its frequency content, with lower frequency signals within the band being attenuated more than higher frequency signals. A final amplification
15 stage 58 sets the volume of the signal, and the signal is then passed over to the implantable portion 12' through a switch 60 and a telemetry channel 66. The implantable portion 12', once it receives the signal, limits its amplitude to a safe value with a clipping circuit 62,
20 converts the signal back to an analog signal using digital-to-analog (D/A) converter 64, and then applies the analog signal to the electrodes that have been configured for the appropriate channel.

Those of skill in the art will recognize that
25 the above description of FIG. 2 is significantly simplified. For example, the telemetry channel 66 typically requires that the information from each channel be reformatted into a serial data stream, or data frame, that is passed serially over to the implantable portion
30 12' through inductively coupled coils. Once received within the implantable portion, such data frame must be processed in an appropriate manner to recover the information for each channel and present such recovered information to the respective electrode pair for that
35 channel. Such telemetry channel details, while

- 15 -

interesting, are not really critical to an understanding of the present invention, except as indicated below.

Further, it is noted that the manner in which the switches 60 are operated plays a significant role in defining the particular speech processing strategy that is employed by the system. For example, if the switches 60 are operated such that only one switch is closed at any instant of time, but at a rapid rate, then the external portion 10' of the stimulation system effectively samples the incoming acoustical signal, one frequency band at a time. Such a strategy, which stimulates only one electrode pair or cochlear location at any instant of time, is known as a "continuous interleaved sampler" (CIS) strategy. In contrast, if the switches 60 are operated such that they are always closed, then the information in that frequency channel is effectively processed continuously. Such a strategy, which may stimulate more or all of the electrode pairs with a respective stimulation waveform at the same time, is known as a "continuous analog" (CA) strategy. In one sense, the present invention may be viewed as a method or technique for controlling the switches 60 of each channel so as to provide much more flexibility in the type of stimulation strategy employed by the implantable portion 12' of the stimulation system.

Referring next to FIG. 3, a block diagram of a preferred embodiment of the system of FIG. 1 is shown. Such preferred embodiment is described fully in the above-referenced patent application. Basically, the preferred embodiment shown in FIG. 3 comprises a speech processor externally wearable system 10 and an implantable cochlear stimulator (ICS) 12. The speech processor system 10 comprises a headpiece 14 and an externally wearable speech processor (SP) 16. The headpiece may be worn behind the ear of a hearing

- 16 -

impaired person and comprises a conventional microphone 18 and an antenna (coil) 20 for transmitting and receiving electromagnetic energy in the form of radio frequency signals or inductively coupled high frequency signals. Such coupling can be restricted to magnetic field coupling only by an electrostatic shield around the coils comprising the antenna 20. In addition, signals from the ICS to the SP on one carrier frequency and from the SP to the ICS on another frequency can be transferred via a single coaxial cable between the headpiece 14 and the SP 16. This can be accomplished by having tuned inductor-capacitor filters for each frequency at each end of the coaxial cable.

The SP 16, powered by a battery 38, is adapted to receive audio signals received by the microphone 18 and to transmit such signals to a conventional audio front end 22 which features automatic gain control (AGC). The audio signals processed by the audio front end 22 are transmitted to a bank of filters 24 for filtering and for generation of a plurality of parallel audio signals. The audio signals are processed by a multiplexer 26 and converted to a series of digital signals by an A-to-D (A/D) converter 28 for application to a microprocessor 30. The microprocessor 30 includes, or is connected to, a suitable memory chip 31 wherein the template means of the present invention may be stored. The filter bank 24 may also be implemented as a group of digital filters, for example in a digital signal processor integrated circuit. In this case the signal flow would be from the audio front end and AGC 22, through an anti-aliasing filter, to an analog to digital converter, then into a digital filter bank 24 and the general processing of microprocessor 30.

The output of the microprocessor 30 is coupled through a custom gate array 32 that converts data from

- 17 -

the microprocessor into a serial bit stream going to a data transmitter 34. The gate array 32 also converts data from a telemetry receiver 36 and the microprocessor 30 to control the power level of and data generated by the data transmitter 34.

As illustrated in Fig. 3, the ICS 12 includes a receiver 40 for receiving data transmissions from the wearable system 10 and a telemetry transmitter 42 for transmitting ICS status indicating and measured signals from the ICS 12 to the wearable system 10 for processing thereby. For example, power level indicating signals transmitted by the telemetry transmitter 42 are received by the telemetry transmitter 36 and processed in the microprocessor 30 and gate array 32 to generate signals controlling the power level of the transmissions from the transmitter 34 to the ICS 12, thereby providing a closed-loop system for optimizing the power levels of the transmission from the wearable system 10 to the ICS 12 and hence conserving the battery 38 and optimizing the voltages generated within the system 10.

In addition to the receiver 40 and transmitter 42, the ICS 12 includes a regulator 44 for receiving a power signal from the receiver 40 to energize a processor 46. Data signals from the receiver 40 are also transmitted to the processor 46 for processing to generate stimulation signals applied to one or more of a plurality of capacitor coupled electrodes 49 in an intra-cochlear electrode 48. The preferred embodiment of the invention provides eight channels, each of which includes two electrodes which may be paired together in order to provide bipolar stimulation. Alternatively, the channels may be configured for monopolar stimulation where a selected one of the two electrodes of the channel is paired with a common reference electrode 51. In addition, various stimulation currents may be applied

- 18 -

simultaneously to two or more monopolar or bipolar sites so as to create a "virtual channel" from the summation of their separate currents within the adjacent tissues.

Generally speaking, in response to control or
5 data signals from the SP 16 the processor 46 selectively monitors voltages of the electrodes and associated circuitry in the processor and generates ICS status indicating and measured signals. For example, the processor 46 monitors the voltage applied to the
10 regulator 44, the impedance of the electrodes and other voltages within the processor to generate the status indicating signals which are sent as data to the telemetry transmitter 42 for transmission to the wearable system 10.

15 More particularly, in the cochlea stimulating system shown in Fig. 3, the signals transmitted to the ICS 12 from the wearable system 10 include electrical power components. Such power components are processed within the receiver 40 through the series regulator 44 to
20 generate a voltage signal which powers the processor 46. The processor 46 selectively monitors the voltage applied to the series regulator and generates a status indicating signal relative to such voltage which is transmitted by the telemetry transmitter 42 and received by the
25 telemetry receiver 36. As previously stated, such information is utilized in the microprocessor 30 and gate array 32 of the SP 16 to control the power level of the transmissions from the data transmitter 34 to the ICS 12.

Turning next to FIG. 4, there is shown the
30 makeup of a typical data frame used with the preferred system of FIG. 3. Such data frame is necessary due to the fact that multiple channels of stimulation information are needed by the ICS 12, yet there is only a single telecommunications channel through which
35 information may be transferred to the ICS. In other

- 19 -

words, use of the data frame shown in FIG. 4 allows parallel data channels to be temporarily reformatted into a serial data channel to facilitate transmission of the information to the ICS.

5 As seen in FIG. 4, the typical data frame is made up of 9 nine-bit words, plus a parity bit and an end-of-frame bit, or a total of 83 bits. The clock rate is such that the overall duration of a complete data frame is about 77 μ sec.

10 The first eight words in the data frame are data words, and each contains amplitude bits (the first eight bits) and a polarity bit. Each data word corresponds to the stimulation information for a given channel. The last word of the data frame, or the ninth
15 word, is a control word. Such word is used to control and/or set various functions within the ICS, e.g., the electrode configuration (bipolar or monopolar) that the ICS will use. The general format of the control word is also shown in FIG. 4.

20 FIG. 5 illustrates how multiple data frames may be used with the system of FIG. 3 to achieve a desired stimulation pattern that repeats itself in cycles. The particular stimulation pattern shown in FIG. 3 approximates a simple CIS strategy because, for the most
25 part, only one electrode pair (channel) is stimulated with a biphasic pulse at any given time. To understand FIG. 5, it is important to recognize that the data word in each data frame specifies the amplitude and polarity for the stimulation current of the corresponding channel.
30 Such amplitude and polarity, once set by a data words, remains unchanged until a new data word, in a new data frame, is received to make a change. Thus, to produce a biphasic stimulation pulse, it is necessary to specify an amplitude and polarity for the channel in a first data
35 frame, specify the amplitude and opposite polarity in a

- 20 -

second data frame, and finally, specify a zero amplitude in a third data frame. If a CIS strategy is employed, as approximated in FIG. 5, then each channel is maintained at a zero amplitude until such time in the cycle as it is
5 that channel's turn to be stimulated in the specified sequence.

As shown in FIG. 5, for example, the specified sequence comprises (starting at the left of the figure) stimulating the electrode pair of channel 2, then channel
10 1, then channel 8, then channel 7, then channel 6, then channel 5, then channel 4, and then channel 3. In a first data frame, Frame A, a positive stimulation current is applied to the electrodes of channel 2. The magnitude of this stimulation current is a function of the sensed
15 acoustic signal falling within the frequency band corresponding to channel 2, and as otherwise processed by the speech processor 16. Note that during data Frame A, not only is channel 2 stimulated, but the stimulation current already present in channel 3 is turned off. This
20 process continues, as shown, with each phase of the biphasic pulse lasting for a time equal to the length of a data frame, and with the complete stimulation cycle requiring 16 data frames.

Still referring to FIG. 5, the numbers 1-9
25 included for each data frame correspond to the nine data words present in each data frame. Thus, when a change is included in the first word of the data frame, such change occurs early in the data frame, whereas a change that occurs in the last word of the data frame, occurs late in
30 the data frame. Given this restriction, one aspect of the present invention relates to mapping the particular electrode pair associated with the words of the data frame so that the electrode pair in contact with the basal end of the cochlea, which receives high frequency
35 information and thus has the most information capacity,

- 21 -

is mapped to the first word in the data frame. The apex of the cochlea, which receives low frequency information and thus has the least information capacity, is mapped to the last word in the data frame. This mapping scheme, in
5 combination with sending partial frames (as described below) advantageously permits a two-to-three times faster update rate to occur at the base of the cochlea than has heretofore been possible.

It should be noted that the stimulation pattern
10 depicted in FIG. 5 represents a simple (non-complex) stimulation pattern. The present invention advantageously utilizes simple and easy-to-define stimulation templates that permit the ICS to generate much more complex stimulation patterns without having to
15 significantly alter the basic operating programs of the speech processor 16, and without having to alter the circuitry of the ICS 12. In fact, the stimulation templates of the present invention may advantageously be used with any type of stimulation system that provides an
20 implanted stimulator that follows the commands of an external processor in a master/slave relationship. That is, so long as the individual channels (or specific tissue stimulation locations as defined by a selected electrode pair) of the implanted stimulator can be set to
25 a specific stimulation current value (including a zero value) as controlled by the external processor, and remain at those values until reset by the external processor to a new stimulation current value, then the present invention can advantageously be used by such
30 system.

To illustrate, FIG. 6 shows one representation of a simple biphasic CIS stimulation template for use with the present invention that provides a CIS stimulation pattern for an eight-channel stimulator
35 device. The template is in the form of a stimulation

- 22 -

table, shown on the right side of FIG. 6, which table may be stored in the memory 31 of the processor 16. The biphasic stimulation currents that result from using such template are represented on the left side of FIG. 6.

- 5 Note that the stimulation table or template comprises rows and columns. Each row represents an increment of time, which increment of time may be set to an appropriate value for the particular application. For the table shown in FIG. 6, it is presumed that all of the
10 increments of time, t_0 - t_{15} , are equal increments of time. However, as will be demonstrated by other possible templates shown below, the time increments need not be equal, but can be specified to any appropriate value.

- Each column of the template table shown in
15 FIG. 6 represents a channel, or stimulation location, Thus, referring to FIG. 6, it is seen that each cell (i.e., each intersection of a row and column) of the template table defines a particular stimulation current that is to be applied to a specific location (the
20 channel, or column) at a particular time (the specified time, or row). The combination of all the cells of the template table thus defines a particular temporospatial stimulation pattern, or a particular cycle of stimulation waveforms, that are to be applied to specific stimulation
25 locations at specific times within the stimulation cycle.

- The numerical values inserted into the cells of the template table represent weighting factors which are to be used to modify the amplitude of the processed signals (derived from the incoming acoustical signal).
30 (It should be noted that data values other than numeric values could also be used for this purpose, e.g., a hexadecimal or other alphanumeric value could be inserted into the cells of the template table as a code.) A null value (blank) table cell indicates that a zero stimulus
35 waveform has been in effect and should continue in effect

- 23 -

for the channel and time specified by the column/row of the template. Typically, the weighting factor will simply be used as a multiplication factor. Thus, if the template table contains a "+1" in a given cell, then that means the processed signal for that channel is to be multiplied by a "+1", with the product of such multiplication serving to define or specify the amplitude of the desired stimulation current to be applied to the electrode pair of the channel at the indicated time increment. An explicit zero, or "0", denotes the time at which a previously non-zero channel is first set to zero output.

It is to be emphasized that the rows and columns of the template table can be reversed and the template table will still serve its intended function of clearly and easily defining a particular stimulation pattern, even a complex stimulation pattern (as is demonstrated below) for use by an ICS or equivalent stimulator device. That is to say, each column of the table may represent an increment of time, and each row of the table may represent a channel, or stimulation location.

Referring to FIG. 6, it is seen that at time t_0 , the first channel, C1, has a value "-1" inserted therein. All other cells in the table at time t_0 are blank (null values), except for C8 (which has a "0" inserted therein), and C9 (which corresponds to the control column or word and which has a "D" inserted therein). The "-1" in the cell corresponding to channel C1 at time t_0 means that whatever magnitude is present in the channel 1 signal at time t_0 will be multiplied by a "-1". The "0" simply means that channel C8 is to be reset back to zero (null) at time t_0 . The "D" in channel C9 (which is the control word channel) means that the 9th word command is to be set to its default value. At time

- 24 -

t1, the weighting factor for channel C1 changes to a "+1". At time t2, the weighting factor for channel C1 is set to "0", and the weighting factor for channel C2 is set to "-1". The timing associated with the actual waveforms for the stimulation currents thus take the form as illustrated on the left side of FIG. 6.

FIG. 7 shows the stimulation template table as in FIG. 6, but for a somewhat more complex biphasic stimulation pattern that includes time delays between phases and channels.

Similarly, FIG. 8 depicts the stimulation template table for a much more complex stimulation pattern that includes asymmetrical and triphasic pulses. Note that the weighting factors are selected so that the sum of the positive factors always equals the sum of the negative factors, thereby assuring a charge balance in the stimulation waveform that is ultimately generated.

FIG. 9 shows the stimulation template table for a stimulation pattern that includes alterphasic pulses. An alterphasic pulse is a pulse as shown for channel C1 and channel C3 -- a pulse of one polarity followed in the next cycle by a pulse of the opposite polarity.

FIG. 9 also illustrates another feature in which a special code "E" is used to indicate that the remainder of the row contains no changes of output state. This permits the microprocessor to save computation time to conserve power or facilitate other concurrent operations.

It is thus seen that the numbers or other alphanumeric codes written into the cells of the template table allow diverse and complex patterns to be specified. Such patterns can easily be produced in real-time by a microprocessor that is programmed to read the cells of the table as input data. Because the possible output states are entirely specified by the template table,

- 25 -

there is no possibility of unexpected delays occurring during real-time execution of the program. This is a critical feature, because the charge-balance of the waveforms produced by each current source depends on
5 computing the weighting coefficients or factors such that the sum of the products of each weighting coefficient times the respective time interval for that row of the template table adds to zero for all weighting
10 coefficients in each column. That is, the amount of time that each of the current sources stays in any particular output state must be predictable and reproducible from cycle to cycle.

As should be evident from an examination of the template tables presented above (and below), the length
15 of a given row represents the length or duration of a data frame. The length of a data frame, in turn, specifies the minimum pulse width that may be included within a biphasic stimulation pulse (or other stimulation waveform). One advantage of the present invention is
20 that means are included within the speech processor for shortening selected rows of the table in order to reduce the number of blank cells in a given row. Such shortening, in turn, thereby reduces the minimum pulse width that may be utilized in the stimulus waveform,
25 thereby allowing a more rapid rate of pulses in the stimulus waveform. When such pulses are applied to the basal electrodes of the cochlea, it is thus possible to convey more information to the cochlea than has previously been possible.

30 Referring next to FIG. 10, a stimulation template is illustrated for a stimulation pattern that includes more frequent narrow biphasic stimulation pulses in some channels, and less frequent wider biphasic stimulation pulses in other channels. Also note that
35 only four of the stimulation channels are used in the

- 26 -

pattern shown in FIG. 10: channels C5, C6, C7 and C8. In use, the C8 channel, which has the most frequent pulses applied thereto, preferably corresponds to the electrode pair placed at the basal end of the cochlea. This is because, as previously indicated, the basal end of the cochlea receives high frequency information and thus has the most information capacity. The time intervals used in FIG. 10 may be much shorter than the time intervals used, e.g., in the templates of Figs. 6-9, so that the overall cycle length in FIG. 10 need not be any longer than, and may even be shorter than, the cycle lengths in Figs. 6-9.

FIG. 11 depicts a stimulation template for a stimulation pattern that provides simultaneous biphasic pulses on two or more channels. Such a pattern allows the overall cycle length to be decreased significantly. The stimulation pattern shown in FIG. 11 is of particular interest because of the delivery of pulses more or less simultaneously at two or more different sites. Note that the CIS strategy is designed to minimize electrotonic interactions between the stimulus currents applied at adjacent sites by delivering brief stimulation pulses in a sequential, interleaved, i.e. non-overlapping manner. It is also desirable, however, to complete the stimulation of all sites in as short a cycle time as possible, permitting the information from the acoustic signal to be sampled and presented at a relatively high rate. In order to sequence through a large number of stimulation sites at a relatively rapid rate, the length of time available to deliver each individual stimulation pulse must be made very short. The efficacy of a given stimulus pulse in activating neurons depends on the product of the magnitude and duration of the current, i.e. the total charge delivered in each phase of the waveform. In order to activate neurons with a very brief

- 27 -

current pulse, the magnitude of the current must be made proportionately higher. Because the electrode contacts and surrounding tissue represent a significant impedance to the flow of electrical current, the applied voltage and dissipated power will also be much higher. The problem is even worse for biphasic stimulus pulses shorter than about 60-80 microseconds because the reverse polarity of the second phase partially cancels the effects of the first phase before the neurons can respond to the first phase.

Advantageously, as shown in FIG. 11, the CIS frame rate for a given number of channels each with a given pulse width can be doubled by stimulating two separate sites at the same time. This violation of the non-overlap requirement for the CIS strategy is useful only if the amount of electrotonic interaction between those sites is minimal. That condition is likely to be met when the simultaneously activated sites are selected to be physically distant from each other and when the intensity of stimulation required to produce a full range of loudness at each site is fairly low. Thus, it is a particular advantage of this invention that the pattern of overlap between pulses at various sites can be readily selected and changed simply by altering the values in the template table rather than reprogramming a new algorithm for each stimulus paradigm.

Referring next to FIG. 12A, there is shown the stimulation template for a stimulation pattern that uses short-interval transmissions to create narrow pulses and a faster overall cycle rate. A special code "S" in each row indicates that no further information will be transmitted in that frame, permitting the duration of the frame to be truncated. This also means that the time intervals used in FIG. 12A need not be equal. Rather, t_0 is shorter than t_1 , which is shorter than t_2 , and so on.

- 28 -

Further, as depicted in FIG. 12A, the weighting factors decrease with increasing time intervals in order to equalize the relative efficacy of the various durations of stimulus pulses created by the changing time intervals. Other codes and features provide additional options regarding the duration of each phase of electrical stimulation according to the programmability of the implanted circuitry that generates the output currents.

Referring next to FIG. 12B, a virtual stimulation strategy is shown wherein eight bandpass filter channels are mapped into only six output stages and electrodes. This is accomplished by creating two virtual channels, identified in FIG. 12B as codes V1 and V3 (a first virtual channel), and V6 and V7 (a second virtual channel). The first virtual channel, V1-V3, is shown in column C2 to indicate that the two output stages C1 and C3 are to be summed in phase according to the weighting coefficients in rows 13 and 14. Similarly, codes V6 and V7, in column C8, indicate that the second virtual channel is comprised of output stages C6 and C7, stimulated out of phase according to the weighting coefficients in rows 15 and 16.

From the above figures, it is seen that a great deal of flexibility may be achieved relative to the stimulation patterns and waveforms that are implemented by the ICS or equivalent stimulator device. For the particular embodiment of the ICS described in the referenced patent application, the following codes and features are supported, as an example of the capabilities of the general scheme of the invention:

First, the output current of each current source remains at a given value unless and until it is explicitly set to a new value, so a special "null" code in the table indicates that no change is

- 29 -

required during a particular interval, obviating the need to recompute the output current during a phase of stimulation that lasts longer than one interval or when the desired output is zero for more than one interval.

Second, if a row of the table contains no non-null codes after a given column, then a special "end" code "E" in the table can be used to signal that no further computations are required in that interval.

Third, if a row of the table contains no non-null codes after a given column, then a special "short interval" code "S" in the table can be used to abridge the normal transmission of information to the implanted electronics and immediately beginning transmitting the output states specified by the next row in the table, resulting in a shorter-than-normal interval for the output states specified in the abbreviated row.

Fourth, if the table contains an extra column for mode control of the implanted electronics, the mode value stored in the template table for each row can be transmitted to the implanted electronics at each interval. Such mode values can, for example, specify that the output current that is requested of one or more of the current sources in the subsequent interval be delayed in its onset or terminated prematurely during the course of that interval, thus creating stimulus phases whose duration is a fraction of the interval represented by each row of the table.

Fifth, the output channel designated by a column of the table may be assigned to a virtual channel composed of two or more other output channels. The virtual channel is identified by the

- 30 -

code "Vn", where n is the number of a real output channel

It should next be pointed out that the template table used by the present invention is a tool to
 5 facilitate abstraction of the desired stimulation pattern and waveforms. Other tools that achieve the same end result may also be used. For example, a list or series specification of desired spatial/temporal events may be
 10 then be used as input data to the microprocessor used within the speech processor. For example, the stimulation pattern and waveforms defined by the template table shown in FIG. 12 may alternately be generated by the following series:

15

$$C_n(t, \text{amplitude}): (2*(n-1), -1), (2*(n-1)+1, 1), (2*(n-1)+2, 0)$$

$$F_t(n, \text{code}): (\text{INT}(t/2)+2, S)$$

where

20

t = step number (t_0 - t_{15}) or frame number;
 n = channel number [1-9] or position in frame;
 code = [S]hort, [D]efault, ... all possible codes.

25

Referring next to FIG. 13, a simplified flow chart is shown that depicts one method (certainly not the only method) by which the above or other stimulation templates may be used within the speech processor of the stimulator system to control the stimulation current
 30 patterns and waveforms generated by the implantable portion of the invention. Each main step of the method depicted in FIG. 13 is represented as a "block", where each block has a reference numeral assigned thereto.

As seen in FIG. 13, an initial step (block 200)
 35 is to define the appropriate operating parameters used by

- 31 -

the microprocessor 30 (FIG. 3) within the external (wearable) processor 16. Such operating parameters may include such items as: the data frame interval (the time interval separating the rows in the template table), the cycle length (the number of rows in the template table), the number of channels to be used (the number of columns in the table), the electrode configuration (bipolar, monopolar, etc.), and the like.

Once the initial operating parameters are defined, a new stimulation cycle begins (block 202). As the new stimulation cycle begins, two parallel paths are initiated. In a first path, the acoustic signal is sampled and processed (block 206). Such processing results in a determination of the magnitude and polarity associated with each channel at the sample time. For the preferred ICS described herein, such processing results in generating the eight data words that make up a data frame. This magnitude/polarity information is then stored as a function of the sample time (block 208). Once such magnitude/polarity data has been obtained for each of the available channels (block 210), then this branch of the stimulation cycle waits for the beginning of the next cycle (block 212), at which time a new sample is taken and the process repeats (blocks 206, 208, 210, 212).

Meanwhile, in the parallel path initiated at the beginning of the stimulation cycle, the data frame is initiated. This is accomplished by retrieving the most recent magnitude/polarity data corresponding to the first channel to be included in the data frame (block 214). Once this data has been retrieved, the appropriate weighting factors or weighting coefficients corresponding to the first channel and time interval are also retrieved (block 216). Such retrieval of the weighting coefficients is greatly facilitated through the use of

- 32 -

the template table or other list as described above. The magnitude/polarity data is then multiplied by the appropriate weighting coefficient (block 218) to produce weighted magnitude/polarity data. Such weighted data effectively defines the desired stimulation current for the current data frame. Accordingly, such weighted data is formatted into the data word of the frame in anticipation of sending the data frame to the ICS. If additional channel information/data is required to complete the frame data (YES branch of block 220), then such information/data is retrieved (blocks 214, 216, 218). If all of the information/data needed within the current frame has been accumulated (NO branch of block 220), then the weighted information/data is transferred to the ICS (block 222). A determination is then made as to whether additional frames are needed to complete the cycle (block 224). If so (YES branch of block 224), then the next data frame is initiated and the process repeats (blocks 204, 214, 216, 218, 220, 222, and 224).

20 If the cycle is complete (NO branch of block 224), i.e., if all of the data frames needed to complete the cycle have been generated, a determination may be made as to whether there is a need to adjust the stimulation template (block 226). Such determination is preferably made in cooperation with the patient, i.e., using feedback from the patient as to how well he or she is discerning certain sounds generated as part of a fitting test. If not, then the next stimulation cycle begins and the process repeats as described above (beginning at block 202).

30 If a need does exist for an adjustment of the stimulation template (YES branch of block 226), then such adjustment is made (block 228). Advantageously, the template table provided by the present invention, or other list of the spatial/temporal events, makes such an

- 33 -

adjustment a very easy task. Such task may be undertaken manually, on a trial and error basis, e.g., by simply changing the weighting factors in the template table; or may be performed systematically following a prescribed
5 adjustment algorithm.

As described above, it is thus seen that the present invention provides a multi-channel stimulation system that facilitates the definition/specification of a wide range of different temporospatial patterns of
10 electrical stimulation current.

It is further seen that the invention allows complex stimulation waveforms to be defined/specified in a very simple manner.

While the invention herein disclosed has been
15 described by means of specific embodiments and applications thereof, numerous modifications and variations could be made thereto by those skilled in the art without departing from the scope of the invention set forth in the claims.

20

- 34 -

CLAIMS

What is claimed is:

- 5 1. A multichannel cochlear prosthesis comprising a speech processor (10) coupled to a cochlear stimulator (12) so that data signals and control signals may be passed therebetween, characterized by:
- 10 the speech processor (10) having template means (30, 31) for storing a set of coefficients that represent a particular temporospatial pattern of stimulus waveforms, means (30, 32, 34, 20) responsive to the set of coefficients stored in the template storage means for generating data and control signals that specify a
- 15 particular temporospatial pattern of controlled stimulus waveforms to be generated by respective channels within the cochlear stimulator; and
- the cochlear stimulator (12) having means (40) for receiving the data and control signals from the
- 20 speech processor; a multiplicity of channels, each having at least one pair of electrodes (49, 51) associated therewith, means (46) for generating a controlled stimulus waveform for each of the multiplicity of channels as a function of said data and control signals
- 25 received from the speech processor, and means (46, 48) for applying the controlled stimulus waveform to at least two of the multiplicity of channels so that the specified controlled stimulus waveform appears across the paired electrodes of at least two channels.
- 30 2. The multichannel cochlear prosthesis of Claim 1 wherein the controlled stimulus waveform applied to at least two of the multiplicity of channels comprises a waveform selected from the group comprising biphasic

- 35 -

pulses, triphasic pulses, asymmetrical pulses, and alterphasic pulses.

3. The multichannel cochlear prosthesis of
5 Claims 1 or 2 wherein the template means (30, 31)
comprises means for generating a table having rows and
columns (FIGS. 6-12B), with each one of the rows or
columns being associated with at least one of the
multiplicity of electrode pairs, and with each one of the
10 other of the columns or rows being associated with an
increment of time such that a consecutive sequence of
such other of the columns or rows represents increasing
time, and wherein the intersection of each row and column
comprises a table cell, and wherein said template means
15 further includes means for inserting an alphanumeric
value in any cell of said table, said alphanumeric value
defining the amplitude and polarity of the stimulus
waveform for the electrode pair and time represented by
the table cell wherein the number is inserted, whereby
20 the template of the temporospatial pattern of stimulus
waveforms specified for a given electrode pair is defined
by the sequence of alphanumeric values inserted in the
column or row of said table corresponding to said given
electrode pair.

25

4. The multichannel cochlear prosthesis of Claim 3
wherein said template means further includes means for
interpreting a specified zero symbol, such as a blank, in
a table cell as specifying a zero stimulus waveform for
30 the electrode pair corresponding to the column or row of
the specified zero symbol at the time corresponding to
the row or column of the specified zero symbol.

5. The multichannel cochlear prosthesis of Claim 4
35 wherein the length of the row or column used to represent

- 36 -

increasing time defines a data frame having a specified duration, which specified duration in turn defines a minimum pulse width that may be utilized in the stimulus waveform.

5

6. The multichannel cochlear prosthesis of Claim 5 wherein said template means further includes means for shortening selected rows or columns of said table to reduce the number of cells containing the specified zero
10 symbol in the row or column, thereby reducing the minimum pulse width that may be utilized in the stimulus waveform, thereby allowing a more rapid rate of pulses in the stimulus waveform.

15

7. The multichannel cochlear prosthesis of any preceding claim wherein a first electrode pair is stimulated with a first temporospatial pattern of stimulus waveforms at the same time that a second electrode pair is stimulated with a second temporospatial
20 pattern of stimulus waveforms,

25

8. The multichannel cochlear prosthesis of any preceding claim wherein the temporospatial pattern of stimulus waveforms comprises a continuous interleaved sampling (CIS) strategy wherein short pulses are applied at a rapid rate to a first electrode pair, and longer pulses are applied at a less frequent rate to a second electrode pair.

30

9. A method of controlling a cochlear stimulator (CS), said CS including a multiplicity of channels, each channel having at least one pair of stimulation electrodes associated therewith and means for generating and applying a stimulation pulse thereto; and means for
35 defining a data frame that defines a time period during

- 37 -

which the multiplicity of channels are stimulated in accordance with a prescribed pattern; said method comprising the steps of:

- (a) specifying a particular type of stimulation waveform that is desired for each channel of the CS during each data frame, said type of stimulation waveform including a specification of a stimulation pulse polarity, magnitude, duration, and time of occurrence within the data frame, the type of stimulation waveform specified for one channel being independent of the type of stimulation waveforms specified for others of the channels, whereby each channel has its own stimulation waveform specified therefor, which stimulation waveform need not be the same as the stimulation waveform specified for another channel, but can be when desired;
- (b) generating and transmitting a control signal to the CS that defines the particular type of stimulation waveform desired for each channel of the ICS; and
- (c) generating the stimulation waveform specified by the control signal for each channel of the ICS during each data frame.

10. The method as set forth in Claim 9 wherein step (a) of specifying the type of stimulation waveform that is desired for each channel comprises
 - generating and storing external to the CS a table having rows and columns, each column or row being associated with one of the multiplicity of channels, and each row or column being associated with an increment of time equal to the duration of the narrowest pulse width to be included within the stimulation waveform, with the sum of the time increments from all of the rows/columns of the table equaling the time period of a data frame, and wherein the intersection of each row and column comprises a table cell, and


- 38 -

inserting an alphanumeric value in the cell of the table that defines the desired relative amplitude and polarity of the stimulus waveform for the channel and frame time corresponding to the table cell, whereby the
5 temporospatial pattern of stimulus waveforms specified for a given channel is defined by the sequence of alphanumeric values inserted in the column/row of the table corresponding to the given channel.

10 11. The method of Claim 10 further including interpreting a designated alphanumeric character in a given table cell as specifying that no change is required in the output of the channel corresponding to the column/row of the given table cell containing the
15 designated alphanumeric character at the frame time corresponding to the row/column of the given table cell containing the designated alphanumeric character.

20 12. The method of Claim 11 further including the step of shortening the frame time by an amount equal to the number of cells in a given row or column of the table that contain nothing but the designated alphanumeric character.

1 / 13

**FIG. 1**

2 / 13




Fig. 2

3 / 13




FIG. 3




FIG. 4




FIG. 5

6 / 13

Simple Biphasic CIS




FIG. 6

Simultaneous Pulses on two or more Channels for Double-Speed CIS




FIG. 11

Biphasic Pulses with Delays between Phases and Channels

TIME	C1	C2	C3	C4	C5	C6	C7	C8	C9
t0	-1								D
t1	1								
t2	0								
t3		-1							
t4		0							
t5		1							
t6		0	-1						
t7			0						
t8			1						
t9			0	-1					
t10				1					
t11				0					
t12					-1				
t13					1				
t14					0				
t15						-1			
t16						1			
t17						0			
t18							-1		
t19							1		
t20							0		
t21								-1	
t22								1	
t23								0	
t24									
t25									





FIG. 7

Asymmetrical and Triphasic Pulses



TIME	C1	C2	C3	C4	C5	C6	C7	C8	C9
t0	-1								D
t1	0.2								
t2	0.2								
t3	0.2	-0.5							
t4	0.2	1							
t5	0.2	-0.5							
t6	0	0	-1						
t7			0.2						
t8			0.2						
t9			0.2	-0.5					
t10			0.2	1					
t11			0.2	-0.5					
t12			0	0	-1				
t13					0.2				
t14					0.2				
t15					0.2	-0.5			
t16					0.2	1			
t17					0.2	-0.5			
t18					0	0	-1		
t19							0.2		
t20							0.2		
t21							0.2	-0.5	
t22							0.2	1	
t23							0.2	-0.5	
t24							0	0	
t25									

FIG. 8

9 / 13

TIME	C1	C2	C3	C4	C5	C6	C7	C8	C9
t10	-1							0	D
t11	0	E							
t12		-1	E						
t13		1	E						
t14		0	-1	E					
t15			0	E					
t16				-1	E				
t17				1	E				
t18				0	-1	E			
t19				1	E				
t110				0	-1	E			
t111					1	E			
t112					0	-1	E		
t113					1	E			
t114						0	-1	D	
t115							1	D	
t116	1							0	D
t117	0	E							
t118		1	E						
t119		-1	E						
t120		0	1	E					
t121			0	E					
t122				1	E				
t123				-1	E				
t124				0	1	E			
t125					-1	E			
t126					0	1	E		
t127						-1	E		
t128						0	1	E	
t129							-1	E	
t130							0	1	D
t131								-1	D

Alterphasic Pulses




FIG. 9

TIME	C1	C2	C3	C4	C5	C6	C7	C8	C9
t10					0			1	D
t11								-1	
t12							1	0	
t13							-1		
t14							0	1	
t15								-1	
t16						1		0	
t17						1			
t18						-1			
t19						-1			
t110						0		1	
t111								-1	
t112							1	0	
t113							-1		
t114							0		
t115								1	
t116								-1	
t117						1		0	
t118						1			
t119						-1			
t120						-1			
t121					1	0			
t122					1				
t123					1				
t124					-1				
t125					-1				
t126					-1				





FIG. 10

Short-Interval Transmissions to create Narrow Pulses
and Faster overall Frame Rates



TIME	C1	C2	C3	C4	C5	C6	C7	C8	C9
t0	-1	S							
t1	1	S							
t2	0	-0.67	S						
t3		0.67	S						
t4		0	-0.50	S					
t5			0.50	S					
t6			0	-0.40	S				
t7				0.40	S				
t8				0	-0.33	S			
t9					0.33	S			
t10					0	-0.29	S		
t11						0.29	S		
t12						0	-0.25	S	
t13							0.25	S	
t14							0	-0.22	
t15								0.22	

FIG. 12A

12 / 13




FIG. 12B

FRAME	C1	C2	C3	C4	C5	C6	C7	C8
1	+1	-	-	-	-	-	-	-
2	-1	-	-	-	-	-	-	-
3	0	-	+1	-	-	-	-	-
4	-	-	-1	-	-	-	-	-
5	-	-	0	+1	-	-	-	-
6	-	-	-	-1	-	-	-	-
7	-	-	0	0	+1	-	-	-
8	-	-	-	-1	-	-	-	-
9	-	-	-	0	0	-1	-	-
10	-	-	-	-	-	0	+1	-
11	-	V1	-	-	-	-	-	-
12	-	V3	-	-	-	0	-1	-
13	+0.5	-	+0.5	-	-	-	0	V6
14	-0.5	-	-0.5	-	-	-	-	V7
15	0	-	0	-	-	-1	+0.5	-
16	-	-	-	-	-	+1	-0.5	-
17	-	-	-	-	-	0	0	-

13 / 13




FIG. 13
SUBSTITUTE SHEET (RULE 26)

INTERNATIONAL SEARCH REPORT

International Application No
PC1/US 96/05854

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 H04R25/00 A61F11/04

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
IPC 6 H04R A61F G10L G06F A61N

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	EP,A,0 247 649 (THE COMMONWEALTH OF AUSTRALIA) 2 December 1987	1,2,9
A	see page 6, line 52 - page 16, line 37 see page 17, line 50 - page 37, line 6 ---	5-8,10
Y	US,A,5 073 939 (VENSKO ET AL.) 17 December 1991	1,2,7-9
A	see column 2, line 23-49 see column 3, line 15 - column 4, line 39 see column 7, line 21-60 see column 11, line 64 - column 12, line 30 see column 16, line 67 - column 18, line 36 --- -/--	3,4,6, 10-12

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

& document member of the same patent family

Date of the actual completion of the international search

8 August 1996

Date of mailing of the international search report

3 0. 08 96

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Zanti, P

INTERNATIONAL SEARCH REPORT

Internat'l Application No
PCT/US 96/05854

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT		
Category	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y A	US,A,4 918 745 (HUTCHISON) 17 April 1990 see column 1, line 6-10 see column 4, line 9-43 see column 5, line 4 - column 6, line 62 see column 9, line 11 - column 16, line 9 ---	1,8 2,5,6,9
Y A	WO,A,95 01709 (THE UNIVERSITY OF MELBOURNE) 12 January 1995 see page 1, line 3 - page 6, line 3 ---	1,2,7,9 8,10
Y A	WO,A,91 03913 (COCHLEAR PTY. & THE UNIVERSITY OF MELBOURNE.) 21 March 1991 see page 1, line 2-22 see page 18, line 24 - page 23, line 34 see page 26, line 14 - page 35, line 23 -----	1,2,9 5-7,10

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 96/05854

Patent document cited in search report	Publication date	Patent family member(s)	Publication date	
EP-A-247649	02-12-87	US-A-	4532930	06-08-85
		AU-B-	563754	23-07-87
		AU-B-	2668384	18-10-84
		AU-B-	595883	12-04-90
		AU-B-	7322787	10-09-87
		AU-B-	597661	07-06-90
		AU-B-	7325187	10-09-87
		CA-A-	1212501	14-10-86
		DE-A-	3485547	09-04-92
		DE-A-	3485926	22-10-92
		EP-A-	0124930	14-11-84
		EP-A-	0241101	14-10-87
		JP-C-	1761599	28-05-93
		JP-B-	4012141	03-03-92
		JP-A-	61001200	07-01-86

US-A-5073939	17-12-91	NONE		

US-A-4918745	17-04-90	NONE		

WO-A-9501709	12-01-95	AU-B-	7064794	24-01-95
		EP-A-	0663137	19-07-95
		JP-T-	8501241	13-02-96

WO-A-9103913	21-03-91	AU-B-	6339290	08-04-91
		CA-A,C	2024845	09-03-91
		DE-D-	69024479	08-02-96
		DE-T-	69024479	30-05-96
		EP-A-	0450004	09-10-91
		US-A-	5095904	17-03-92
		US-A-	5271397	21-12-93
